7 Electrical Parts List

❋ You can search for updated part codes through ITSELF web site.
URL : http://itself.sec.samsung.co.kr/

7-1-1 LW17M24C Main PCB Parts

Level	Code No.	Loc. No.	Description	Specification	Remarks
0	VC17EO				
1	S5-VC17EO	-	2	SEC,EH-L05(ZPD)	-
3	BN94-00539S	-	ASSY PCB MAIN	VC17EO	SNA
4	0204-002420	CIS3	SOLVENT	1M-1000,C3H70H,96,-,-	SNA
4	0204-002426	CIS4	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG,-	SNA
4	2801-003959	X702	CRYSTAL-UNIT	0.032768MHz,20ppm,28-AAY,12.5pF,35kohm,BK	SA
4	2904-001179	FT800	FILTER-SAW	36.125MHz,-,32.65-39.6MHz/0.5dB,SIP5K,+-0MHz/21.8dB,31.25MHz/37dB	SA
4	3701-001294	CN908	CONNECTOR-DSUB	15P,3R,FEMALE,STRAIGHT,AUF	SA
4	3705-001331	CIS6	CONNECTOR-COAXIAL	PAL,ADAPTOR(J/J),-,75ohm,-	SA
4	3711-004712	CN100	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	SA
4	3722-000158	CN900	JACK-PIN	1P,3.4mm,SN,YEL,-	SA
4	3722-000498	CN902	JACK-SCART	21P,-,SN,BLK,NO	SA
4	3722-001061	CN909	JACK-PHONE	1P,3.6PI,AG,BLK,N	SA
4	3722-001734	CN903	JACK-VHS	4P,-,SN,BLK,-	SA
4	3722-001846	U1913	JACK-PIN	2P,8.3MM,AU,WHT/RED,-	SA
4	BN40-00049A	TU01	TUNER	TMQZ6-416A,VE15,PAL BG,PAL HYPER,38.9MHz,75 ohm,75 ohm,PHONE-JACK,ASYMM,5V,TR	SA
4	BN97-00362L	MICOM	ASSY MICOM	VC17EO,PM39LV020,T-VNC17PEU,2004.03.24,1107-001495	SNA
5	1107-001495	IC703	IC-FLASH MEMORY	AT49BV002AN-70JI,256Kx8Bit,PLCC,32P,14x11.5mm,70nS,2.7/3.6V,-,-,-40to+85C,50uA,-	SA
4	BN97-00384A	-	ASSY SMD	VC17EO	SNA
5	0401-001056	D200	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D600	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D701	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D702	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D800	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D908	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D909	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D910	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D912	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D913	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D915	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D948	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D949	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D951	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D952	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D953	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D954	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D955	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D956	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D957	DIODE-SWITCHING	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0402-000553	D101	DIODE-RECTIFIER	SS24,40V,2.0A,DO-214AA	SA
5	0402-000553	D102	DIODE-RECTIFIER	SS24,40V,2.0A,DO-214AA	SA
5	0403-000579	D904	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D916	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D917	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D918	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D919	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D920	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D928	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D950	DIODE-ZENER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-001048	D944	DIODE-ZENER	BZX84C16,15.3-17.1V,225MW,SOT-23,TP	SA
5	0403-001052	D603	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D604	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D900	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D901	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D902	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D903	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D905	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D906	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D911	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D914	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D921	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D922	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	0403-001052	D923	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D924	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D925	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D926	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D927	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D930	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D932	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D934	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D936	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D940	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D941	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D942	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D945	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D946	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D947	DIODE-ZENER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001425	D201	DIODE-ZENER	BZX84C33,31-35V,350MW,SOT-23,TP	SA
5	0403-001435	D602	DIODE-ZENER	QZX363C5V6,5.32-5.88V,200MW,SOT-363,TP	SA
5	0407-000123	D601	DIODE-ARRAY	DAN202K,80V,100MA,CA2-3,SOT-23,TP	SA
5	0407-000123	D907	DIODE-ARRAY	DAN202K,80V,100MA,CA2-3,SOT-23,TP	SA
5	0501-000280	Q801	TR-SMALL SIGNAL	KSA1182,PNP,150mW,SOT-23,TP,70	SA
5	0501-000280	Q802	TR-SMALL SIGNAL	KSA1182,PNP,150mW,SOT-23,TP,70	SA
5	0501-000280	Q803	TR-SMALL SIGNAL	KSA1182,PNP,150mW,SOT-23,TP,70	SA
5	0501-000280	Q804	TR-SMALL SIGNAL	KSA1182,PNP,150mW,SOT-23,TP,70	SA
5	0501-000342	Q200	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q600	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q601	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q602	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q603	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q800	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q902	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	SA
5	0501-000344	Q809	TR-SMALL SIGNAL	KSC1623-G,NPN,200mW,SOT-23,TP,	SA
5	0501-002080	Q100	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q101	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q104	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q805	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q810	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q900	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	SA
5	0801-002267	IC903	IC-CMOS LOGIC	74LCX14,-,SOIC,14P,150MIL,-,TP,-,-,-,3.6V,-40TO+85C,-,5.5V,-,-,24MA	SA
5	0801-002716	IC902	IC-CMOS LOGIC	74LCX157,MULTIPLEXER,SOIC,16P,150MIL,QUAD,TP,PLASTIC,-,-,0V,-40TO+85C,-,0V,10UA,	SA
5	0909-001036	IC706	IC-REAL TIME CLOCK	DS1337S,-,SO,8P,150MIL,400KHZ,TP,CMOS,PLASTIC,3.3V,-,-40TO+85C,-,-,-,-,-	SA
5	1001-001082	IC501	IC-VIDEO SWITCH	BA7657F,-,SOP,24P,300MIL,SINGL	SA
5	1003-001713	IC704	IC-LCD CONTROLLER	GM2221,PQFP,208P,-,-,-,TR,PLASTIC,3.3V,0to+70C,-,-,-	SA
5	1103-000129	IC900	IC-EEPROM	24C02,256x8,SOP,8P,5x4mm,4.5/5.5V,0to+70C	SA
5	1103-001314	IC705	IC-EEPROM	24C16,2Kx8,SOP,8P,5x4mm,2.7/5.5V,-40to+85C	SA
5	1103-001314	IC805	IC-EEPROM	24C16,2Kx8,SOP,8P,5x4mm,2.7/5.5V,-40to+85C	SA
5	1201-001495	IC601	IC-AUDIO AMP	7050,SOP,8P,150MIL,DUAL,26DB,PLASTIC,6V,0.25W,-,40DB,-,-,20NA,-	SA
5	1201-001980	IC600	IC-AUDIO AMP	TDA7266D,SO,20P,16X11.1MM,-,26DB,PLASTIC,12V,25W,0TO+70C,-,-,-,-,-,TP	SA
5	1203-001816	IC109	IC-POSI.FIXED REG.	78M08,TO-252,3P,-,PLASTIC,7.7/8.3V,1.0W,-40TO+85C,0.5A,-,TP	SA
5	1203-001824	IC300	IC-VOL. DETECTOR	7042,SOT-89,3P,-,PLASTIC,4.05V/4.35V,500MW,-30TO+75C,20MA,-,TP	SA
5	1203-002842	IC101	IC-POSI.FIXED REG.	AP1117D-33A,TO-252,3P,6.7X5.6MM,PLASTIC,3.235/3.365V,-,0TO+150C,1A,-,TP	SA
5	1203-002842	IC111	IC-POSI.FIXED REG.	AP1117D-33A,TO-252,3P,6.7X5.6MM,PLASTIC,3.235/3.365V,-,0TO+150C,1A,-,TP	SA
5	1203-002844	IC105	IC-POSI.FIXED REG.	AP1117D-18A,TO-252-3L,3P,6.7X5.6MM,PLASTIC,1.764/1.836V,-,0TO+150C,1A,-,TP	SA
5	1203-002844	IC112	IC-POSI.FIXED REG.	AP1117D-18A,TO-252-3L,3P,6.7X5.6MM,PLASTIC,1.764/1.836V,-,0TO+150C,1A,-,TP	SA
5	1203-003015	IC108	IC-DC/DC CONVERTER	MP1410ES,SOIC,8P,4.9x3.9mm,PLASTIC,2.5/5V,-,-20to+85C,2A,-,TP	SA
5	1203-003015	IC110	IC-DC/DC CONVERTER	MP1410ES,SOIC,8P,4.9x3.9mm,PLASTIC,2.5/5V,-,-20to+85C,2A,-,TP	SA
5	2007-000052	R738	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R739	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R8126	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R915	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R916	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000070	R205	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R207	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R208	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R209	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R311	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R312	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R734	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R781	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R803	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R8104	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R8105	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R837	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R841	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R842	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R845	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R850	R-CHIP	0ohm,5%,1/10W,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2007-000070	R851	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R856	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R857	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R859	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R860	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R862	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R863	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R866	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R882	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R883	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R884	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R885	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R886	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R887	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R889	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R890	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R891	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R967	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000071	R835	R-CHIP	22ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R122	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R166	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R170	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R203	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R204	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R602	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R603	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R703	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R705	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R707	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R709	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R710	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R711	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R712	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R714	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R715	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R716	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R717	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R718	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R719	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R720	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R727	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R728	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R729	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R752	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R753	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R770	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R771	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R772	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R775	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R776	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R777	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R778	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R779	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R8019	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R8108	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R871	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R880	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R881	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R900	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R901	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R905	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R907	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R910	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R911	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R912	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R920	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R921	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R923	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R950	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R951	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R952	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R954	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R955	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R956	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R957	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R958	R-CHIP	100ohm,5%,1/10W,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2007-000074	R959	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R960	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R961	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R962	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R963	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R964	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R968	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000075	R940	R-CHIP	220ohm,5%,1/10W,TP,1608	SA
5	2007-000075	R942	R-CHIP	220ohm,5%,1/10W,TP,1608	SA
5	2007-000076	R200	R-CHIP	330ohm,5%,1/10W,TP,1608	SA
5	2007-000077	R802	R-CHIP	470ohm,5%,1/10W,TP,1608	SA
5	2007-000078	R604	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R611	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R619	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R623	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R725	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R839	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R864	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R927	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R928	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R931	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R932	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000080	R512	R-CHIP	2Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R624	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R625	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R8145	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R858	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000082	R8017	R-CHIP	3.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000082	R8106	R-CHIP	3.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000082	R934	R-CHIP	3.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R600	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R601	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R607	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R609	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R800	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R801	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R8119	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R8120	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R855	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R914	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R924	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R929	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R930	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R173	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R852	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R853	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R114	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R128	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R165	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R174	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R516	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R605	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R606	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R608	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R610	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R614	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R615	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R704	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R706	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R713	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R742	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R745	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R746	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R747	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R748	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R749	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R8121	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R8143	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R8144	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R821	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R879	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R933	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R944	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R965	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R966	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000091	R167	R-CHIP	12Kohm,5%,1/10W,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2007-000093	R612	R-CHIP	20Kohm,5%,1/10W,TP,1608	SA
5	2007-000093	R613	R-CHIP	20Kohm,5%,1/10W,TP,1608	SA
5	2007-000093	R616	R-CHIP	20Kohm,5%,1/10W,TP,1608	SA
5	2007-000094	R202	R-CHIP	22Kohm,5%,1/10W,TP,1608	SA
5	2007-000100	R514	R-CHIP	68Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R116	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R120	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R121	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R127	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R201	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R211	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000103	R617	R-CHIP	120Kohm,5%,1/10W,TP,1608	SA
5	2007-000107	R510	R-CHIP	470Kohm,5%,1/10W,TP,1608	SA
5	2007-000113	R838	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R843	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R854	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000121	R8109	R-CHIP	820ohm,5%,1/10W,TP,1608	SA
5	2007-000234	R896	R-CHIP	1.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000239	R773	R-CHIP	1.5Kohm,1%,1/10W,TP,1608	SA
5	2007-000239	R774	R-CHIP	1.5Kohm,1%,1/10W,TP,1608	SA
5	2007-000309	R620	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R621	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R827	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R830	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R833	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R732	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R733	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R740	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R817	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R818	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R819	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R836	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R840	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R849	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R897	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R925	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000458	R808	R-CHIP	18Kohm,5%,1/10W,TP,1608	SA
5	2007-000539	R828	R-CHIP	200ohm,5%,1/10W,TP,1608	SA
5	2007-000539	R831	R-CHIP	200ohm,5%,1/10W,TP,1608	SA
5	2007-000539	R834	R-CHIP	200ohm,5%,1/10W,TP,1608	SA
5	2007-000570	R926	R-CHIP	220OHM,1%,1/10W,DA,TP,1608	SA
5	2007-000608	R737	R-CHIP	240ohm,5%,1/10W,TP,1608	SA
5	2007-000643	R826	R-CHIP	270ohm,5%,1/10W,TP,1608	SA
5	2007-000643	R829	R-CHIP	270ohm,5%,1/10W,TP,1608	SA
5	2007-000643	R832	R-CHIP	270ohm,5%,1/10W,TP,1608	SA
5	2007-000659	R899	R-CHIP	27ohm,5%,1/10W,TP,1608	SA
5	2007-000708	R169	R-CHIP	3.9Kohm,1%,1/10W,TP,1608	SA
5	2007-000882	R8102	R-CHIP	4.7ohm,5%,1/10W,TP,1608	SA
5	2007-000913	R171	R-CHIP	43Kohm,5%,1/10W,TP,1608	SA
5	2007-000939	R115	R-CHIP	47Kohm,1%,1/10W,TP,1608	SA
5	2007-000965	R168	R-CHIP	5.1Kohm,5%,1/10W,TP,1608	SA
5	2007-000965	R172	R-CHIP	5.1Kohm,5%,1/10W,TP,1608	SA
5	2007-001002	R8101	R-CHIP	510ohm,5%,1/10W,TP,1608	SA
5	2007-001044	R618	R-CHIP	56ohm,5%,1/10W,TP,1608	SA
5	2007-001044	R622	R-CHIP	56ohm,5%,1/10W,TP,1608	SA
5	2007-001101	R888	R-CHIP	62ohm,5%,1/10W,TP,1608	SA
5	2007-001134	R8100	R-CHIP	68ohm,5%,1/10W,TP,1608	SA
5	2007-001164	R501	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R503	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R506	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R735	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R736	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R741	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R902	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R903	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R904	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R917	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R918	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R919	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R946	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001167	R906	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R908	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R909	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R945	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001179	R210	R-CHIP	8.2Kohm,5%,1/10W,TP,1608	SA
5	2011-000002	RA711	R-NET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2011-000002	RA712	R-NET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA713	R-NET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA714	R-NET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA715	R-NET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000881	RA800	R-NET	33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6x0.5mm	SA
5	2011-000881	RA808	R-NET	33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6x0.5mm	SA
5	2203-000041	C540	C-CER,CHIP	0.01NF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000041	C541	C-CER,CHIP	0.01NF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000041	C542	C-CER,CHIP	0.01NF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000140	C119	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C120	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C132	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C286	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C314	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C316	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C318	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C334	C-CER,CHIP	1.5nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000189	C107	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C117	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C118	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C143	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C163	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C175	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C179	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C183	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C190	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C203	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C217	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C607	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C609	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C615	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C620	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C745	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C754	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C766	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C769	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C802	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C808	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C810	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C817	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C818	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C819	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C820	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C821	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C822	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C823	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C824	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C825	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C827	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C828	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C829	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C839	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C910	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C918	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C919	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C920	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C939	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000189	C940	C-CER,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	SA
5	2203-000236	C182	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C189	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C208	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C209	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C922	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C933	C-CER,CHIP	0.1NF,5%,50V,C0G,TP,1608	SA
5	2203-000257	C180	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C181	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C187	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C188	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C200	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C205	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C212	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C502	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C743	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C744	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C750	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C755	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2203-000257	C756	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C757	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C758	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C809	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C811	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C812	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C846	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C936	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C938	C-CER,CHIP	10nF,10%,50V,X7R,TP,1608	SA
5	2203-000491	C202	C-CER,CHIP	2.2nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000491	C611	C-CER,CHIP	2.2nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000491	C612	C-CER,CHIP	2.2nF,10%,50V,X7R,TP,1608,-	SA
5	2203-000626	C804	C-CER,CHIP	0.022nF,5%,50V,C0G,TP,1608	SA
5	2203-000626	C805	C-CER,CHIP	0.022nF,5%,50V,C0G,TP,1608	SA
5	2203-000697	C909	C-CER,CHIP	0.002NF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000697	C915	C-CER,CHIP	0.002NF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000697	C916	C-CER,CHIP	0.002NF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000697	C917	C-CER,CHIP	0.002NF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000783	C900	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C901	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C907	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C908	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C911	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C913	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C931	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C932	C-CER,CHIP	0.33NF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C902	C-CER,CHIP	0.033NF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C903	C-CER,CHIP	0.033NF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C904	C-CER,CHIP	0.033NF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C905	C-CER,CHIP	0.033NF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C906	C-CER,CHIP	0.033NF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C934	C-CER,CHIP	0.033NF,5%,50V,C0G,TP,1608	SA
5	2203-000888	C204	C-CER,CHIP	4.7nF,10%,50V,X7R,TP,1608	SA
5	2203-000972	C207	C-CER,CHIP	47nF,10%,16V,X7R,TP,1608	SA
5	2203-001052	C813	C-CER,CHIP	0.56nF,10%,50V,X7R,TP,1608	SA
5	2203-001052	C814	C-CER,CHIP	0.56nF,10%,50V,X7R,TP,1608	SA
5	2203-001052	C816	C-CER,CHIP	0.56nF,10%,50V,X7R,TP,1608	SA
5	2203-001086	C727	C-CER,CHIP	0.005nF,0.25pF,50V,NP0,TP,1608	SA
5	2203-001086	C728	C-CER,CHIP	0.005nF,0.25pF,50V,NP0,TP,1608	SA
5	2203-001402	C614	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	SA
5	2203-001402	C617	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	SA
5	2203-001402	C618	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	SA
5	2203-001402	C621	C-CER,CHIP	220nF,+80-20%,16V,Y5V,TP,1608	SA
5	2203-001607	C206	C-CER,CHIP	0.22nF,5%,50V,NP0,-,1608	SA
5	2203-001652	C616	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	SA
5	2203-001652	C619	C-CER,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	SA
5	2203-001656	C121	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C131	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C287	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C315	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C317	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C319	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C335	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C337	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-001656	C521	C-CER,CHIP	0.47nF,5%,50V,NP0,TP,1608	SA
5	2203-005005	C228	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C235	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C524	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C526	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C529	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C530	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C533	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C535	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C704	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C705	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C706	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C707	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C709	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C710	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C711	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C713	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C716	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C718	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C719	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C720	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C721	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2203-005005	C722	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C724	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C725	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C726	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C729	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C730	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C731	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C732	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C733	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C734	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C735	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C736	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C737	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C738	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C739	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C740	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C741	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C742	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C747	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C749	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C759	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C760	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C764	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C768	C-CER,CHIP	100nF,10%,16V,X7R,TP,1608	SA
5	2203-005065	C600	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005065	C603	C-CER,CHIP	1000nF,+80-20%,10V,Y5V,-,1608	SA
5	2203-005194	C714	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C715	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C748	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C751	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C752	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C753	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-006036	C601	C-CER,CHIP	680NF,+80-20%,16V,Y5V,TP,1608	SA
5	2203-006036	C602	C-CER,CHIP	680NF,+80-20%,16V,Y5V,TP,1608	SA
5	2402-000108	C306	C-AL,SMD	10uF,20%,16V,WT,TP,4.3x4.3x5.4	SA
5	2402-000108	C837	C-AL,SMD	10uF,20%,16V,WT,TP,4.3x4.3x5.4	SA
5	2402-000135	C605	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C610	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C835	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C836	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C935	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C937	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000144	C834	C-AL,SMD	3.3UF,20%,50V,GP,TP,4.3X4.3X5.4	SA
5	2402-000170	C101	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C102	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C115	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C213	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C305	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C847	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C921	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000176	C116	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C122	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C123	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C124	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C125	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C126	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C127	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C128	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C129	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C130	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C508	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C509	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C512	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C514	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C517	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C518	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C838	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-001006	C833	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C840	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C841	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C842	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C843	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C844	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C845	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001042	C109	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C111	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2402-001042	C112	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C113	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C178	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C201	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C210	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C604	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C606	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C608	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C613	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C622	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C712	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C800	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001044	C184	C-AL,SMD	100UF,20%,25V,GP,TP,8.3X8.3X6.3MM	SA
5	2402-001044	C191	C-AL,SMD	100UF,20%,25V,GP,TP,8.3X8.3X6.3MM	SA
5	2402-001070	C193	C-AL,SMD	470uF,20%,16V,GP,TP,10x10.2,-	SA
5	2402-001081	C110	C-AL,SMD	100uF,20%,25V,WT,TP,8.3x8.3x10	SA
5	2402-001086	C114	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001086	C765	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001153	C723	C-AL,SMD	100UF,20%,6.3V,WI,TP,6.3X5.8MM	SA
5	2402-001155	C623	C-AL,SMD	47UF,20%,16V,WT,TP,6.3X5.2MM	SA
5	2409-001049	C523	C-ORGANIC	47UF,20%,6.3V,FX,TP,5X5.9MM,-	SA
5	2409-001049	C717	C-ORGANIC	47UF,20%,6.3V,FX,TP,5X5.9MM,-	SA
5	2409-001051	C194	C-ORGANIC	82UF,20%,6.3V,WT,TP,6.3*5.9MM,2.1	SA
5	2409-001051	C708	C-ORGANIC	82UF,20%,6.3V,WT,TP,6.3*5.9MM,2.1	SA
5	2409-001065	C185	C-ORGANIC	82UF,20%,16V,WT,TP,8X6.9MM,-	SA
5	2409-001065	C192	C-ORGANIC	82UF,20%,16V,WT,TP,8X6.9MM,-	SA
5	2703-000185	L803	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L804	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L902	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L903	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L904	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L905	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L908	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L909	INDUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000222	L802	INDUCTOR-SMD	560nH,10%,2012	SA
5	2703-000392	L801	INDUCTOR-SMD	10uH,5%,4532	SA
5	2703-000398	L900	INDUCTOR-SMD	10uH,10%,3225	SA
5	2703-000398	L901	INDUCTOR-SMD	10uH,10%,3225	SA
5	2703-000398	L906	INDUCTOR-SMD	10uH,10%,3225	SA
5	2703-000398	L907	INDUCTOR-SMD	10uH,10%,3225	SA
5	2703-000417	L201	INDUCTOR-SMD	220uH,5%,3225	SA
5	2703-001426	L202	INDUCTOR-SMD	680uH,20%,7070	SA
5	2703-001778	FT131	INDUCTOR-SMD	3.3uH,20%,3225	SA
5	2703-002327	L200	INDUCTOR-SMD	3.9uH,5%,3225	SA
5	2801-003667	X701	CRYSTAL-SMD	14.31818MHz,30ppm,28-AAN,16,50ohm,TP	SA
5	2801-004004	X800	CRYSTAL-SMD	20.25MHz,20ppm,28-AAN,13pF,25ohm,TP	SA
5	2901-001114	FT104	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT105	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT106	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT107	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT108	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT109	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT110	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT111	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT112	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT113	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT500	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT701	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT702	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT703	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT704	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT705	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT706	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT708	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT710	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	2901-001114	FT802	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	SA
5	3301-001145	17INCH	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT100	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT101	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT102	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT11	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT118	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT126	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT127	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT130	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT144	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	3301-001145	FT200	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	PAL	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3704-000249	IC702	SOCKET-IC	32P,PLCC,SN,1.27mm	SA
5	3711-002046	CN905	CONNECTOR-HEADER	BOX,12P,1R,1.25MM,SMD-S,SN,WHT	SA
5	3711-005291	CN601	CONNECTOR-HEADER	BOX,2P,1R,2MM,SMD-A,SN,WHT	SA
5	3711-005292	CN600	CONNECTOR-HEADER	BOX,3P,1R,2MM,SMD-A,SN,WHT	SA
5	3711-005470	CN700	CONNECTOR-HEADER	BOX,30P,1R,1.25mm,SMD-A,Sn+Pb,IVR	SA
5	3711-005471	CN907	CONNECTOR-HEADER	BOX,12P,1R,1.25mm,SMD-A,Sn+Pb,IVR	SA
5	BN27-00009A	FT128	COIL CHOKE	SMD 12X12X6,EOS,33UH,15%,-0.12Ω MAX,2A,DR10X5.0MM,18.5TS,12X12X6,1.8MM,1UEW 0.	SA
5	BN27-00009A	FT145	COIL CHOKE	SMD 12X12X6,EOS,33UH,15%,-0.12Ω MAX,2A,DR10X5.0MM,18.5TS,12X12X6,1.8MM,1UEW 0.	SA
5	BN41-00471A	MP1.0	PCB MAIN	VE17UO,4,1.6,160*160,VE17	SNA
5	BN97-00360J	MICOM1	ASSY MICOM	VE15EO,VCT49XYF,P-VNCPEU,2004-01.27,BN09-00006A	SA
6	BN09-00006A	IC802	IC MICOM	VCT4973-XM C7,144,3.3V,PAL Nicam,PMQFP,TR,0 to +70	SNA
2	BN91-00807E	-	ASSY SHIELD	NEW	SNA
3	6003-000117	SH/TUNER+SH/PAN	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
3	6003-000259	SH/PAN+C/F	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
3	6003-000259	SH/PAN+IP/PCB	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
3	6003-000259	SH/PAN+M/PCB	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
3	6003-000277	SH/PAN+IP/PCB	SCREW-TAPTITE	BH,+,B,M3,L12,ZPC(YEL),SWRCH18	SNA
3	BN39-00474A	CIS	LEAD CONNECTOR	KD17NS,UL1571#30,UL/CSA,30P,130MM,#30,FI-X30H,12507HS-30L,BK,1571#30,SJ03-01-536	SNA
3	BN44-00111B	CIS	IP BOARD	IP-49135A(T),VE17*(VENICE),1.9mA,7.3mA,48KHZ,4,90V/264VAC,+13V/+5.1V,0 to +50, -	SA
3	BN61-00720A	CIS	HOLDER-INVERTOR	GY17LS,ABS PC ,BLK	SNA
3	BN61-01370A	CIS	HOLDER-JACK	VENICE 17",ABS V0,T3.0	SNA
3	BN96-01364A	CIS	ASSY MISC P-BRKT PANEL	VENICE 17"	SNA
4	BH68-30003C	CIS	LABEL-00,HIGH,VOLTAGE	SS,ART 100G,30*33,YEL	SNA
4	BN63-01318A	CIS	SHIELD-PANEL(EH)	LT17M2,SECC,T1.0	SNA
4	BN63-01474A	CIS	FELT-STAND	VENICE 20",FELT,T1.0,10,15	SNA
3	BN96-01395A	CIS	ASSY MISC P-SHIELD TUNER	VE15EO,SPTE T0.5	SNA
2	BN92-01044G	-	ASSY LABEL	VE15EO	SNA
3	AA68-50502A	LABEL	LABEL-00,CONFORMATION	W/P100(G),CTV,ITALY,170x110,BL	SNA
3	BN68-00614A	LABEL	LABEL RATING-00	ALL,SS,PE,T0.05,90*45,BLK,POLYESTER,NO SILK	SNA
2	BN92-01068M	-	ASSY BOX	VC17EO	SNA
3	BH68-00329D	BOX	LABEL BAR CODE-01	NO CE,NO WT`Y,MPRII,LABEL-BARCODE,MOJO 90G,90,95,WHT	SNA
3	BH75-10529C	BOX	UNIT-HANDLE/PACKING	S/M170MP,PE-LD,PE-HD,-,WHITE,-	SA
4	BN72-60001A	CIS	LEVER-TOP	LSD210TL,PE-LD,WHITE,TFT_LCD	SNA
4	BN72-60002C	CIS	LEVER-BOTTOM	S/M170MP,PE-HD,BLUE	SNA
3	BN69-00847D	BOX	BOX-00	VC17E*,SW4 A YEL,EUROPE(CIS)	SNA
2	BN92-01071B	-	ASSY P/MATERIAL	VC17UO	SNA
3	6902-000379	P/M	BAG AIR	HDPE,T0.2,L1800,W1000,TRP,,,PAPER	SNA
3	6902-000520	P/M	BAG PE	HDPE/NITRON(DOUBLE),T0.015/T0.5(DOUBLE),W700,L700,TRP,28 LANGUAGE,2-	SNA
3	6902-000604	P/M	BAG WRAPPING	LDPE,T0.02,W500,L10000,TRP,-,-	SNA
3	6902-000609	P/M	BAG ROLL	LDPE,T0.05,W2400,L1000,TRP,-,-	SNA
3	BH69-00457B	P/M	PACKING-PAD BOTTOM	GH15,FOAM,T3.0,930,1000	SNA
3	BH69-40303A	P/M	PACKING-PALLET	CST7677,WOOD,-,-,W1070,L1050,H120,-,-,-	SNA
3	BH69-40321A	P/M	PACKING-PAD	SW-4,W2155*L140,-,DEC,-,-,-,-,	SNA
3	BN68-00129A	P/M	LABEL SHIPPING-00	-,LABEL SHIPPING,ART-PAPER,100G,-,WHT,BLACK,-,-,-	SNA
3	BN69-00140P	P/M	PAD-PALLET COVER	SUN15,SW,1000*3780,1310,-,-,-,-,-	SNA
3	BN69-00140T	P/M	PAD-PALLET COVER	SUN(LSA810),SW,900,3760,-,-,-,-,-	SNA
3	BN69-00808A	P/M	CUSHION-L,R	LT17M2,EPS M50	SNA
2	BN92-01072A	-	ASSY ACCESSORY	VC17EO	SNA
3	BN59-00437A	ACCESSORY	REMOCON	TM79,Single Micom,36,EX,NT,EX,VENICE	SA
3	BN96-00952W	UNIT/ACCESSORY	ASSY ACCESSORY	VE15EO	SA
4	6801-001014	ACCESSORY	CARD-REGISTRATION	XEU,ENG,MOJO100,L150,W392,-,-	SNA
4	6801-001015	ACCESSORY	CARD-REGISTRATION	XEG,GERMAN,MOJO100,L150,W392,-,-	SNA
4	6801-001016	ACCESSORY	CARD-REGISTRATION	XEF,FRENCH,MOJO100,L150,W392,-,-	SNA
4	6801-001017	ACCESSORY	CARD-REGISTRATION	XEC,SPANISH,MOJO100,L150,W392,-,-	SNA
4	6801-001018	ACCESSORY	CARD-REGISTRATION	XET,ITALY,MOJO100,L150,W392,-,-	SNA
4	6801-001019	ACCESSORY	CARD-REGISTRATION	XEN,DUTCH,MOJO100,L150,W392,-,-	SNA
4	6801-001020	ACCESSORY	CARD-REGISTRATION	XEP,PORTUGAL,MOJO100,L150,W392,-,-	SNA

Level	Code No.	Loc. No.	Description	Specification	Remarks
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA
4	AA68-00291A	ACCESSORY	MANUAL-S/NETWORK	-,SPANISH,-,B5,W/P100G,-	SNA
4	AA68-01092B	ACCESSORY	MANUAL-S/NETWORK	,ITA,B5,W/P100(G),1,1P	SNA
4	AA68-03242A	ACCESSORY	MANUAL-01,SAFETY GUIDE	NT/PAL ALL MODEL,E/F/S/I/G/SC/ST/J/P,R,B5	SNA
4	BN68-00514A	ACCESSORY	MANUAL-WARRANTY CARD	PDP/LCD TV,EN,FR,DE, ETC,W/P 120g	SNA
4	BN68-00633C	ACCESSORY	MANUAL USERS-02	LW15/17/20M,SAMSUNG,E/F/G/D/I/S/P,W.Europe,Mojo 120/100g,B5	SNA
3	BN96-01270A	ACCESSORY	ASSY MISC P-BRKT WALL	VE15UO	SNA
4	BN61-01162A	CIS	BRACKET-WALL	VE15,SECC,2.0	SNA
4	BN96-01272A	CIS	ASSY MISC P-SCREW	VE15UO	SNA
3	BN96-01296G	UNIT/ACCESSORY	ASSY ACCESSORY	VC17EO	SNA
4	3903-000145	ACCESSORY	CBF-POWER CORD	DT,EU,FP3/YES,U(IEC C13-RA),250/250V,10-16/10A,BLK,1830MM,-,H05VV-F 3X1.0MM^2,FL	SA
4	4301-000121	ACCESSORY	BATTERY-MN	1.5V,-,AAA,10.5x44.5m,HOLDER	SA
4	6902-000110	ACCESSORY	BAG PE	LDPE,T0.05,L356,W240,TRP,28,2,PE MARK	SNA

7-1-2 LW17M24C Others

Level	Code No.	Loc. No.	Description	Specification	Remarks
2	BN90-00647X	-	ASSY COVER FRONT	VC17EO	SNA
3	6003-001003	C/F+C/R	SCREW-TAPTITE	BH,+,B,M4,L12,ZPC(BLK),SWRCH18	SA
3	BN96-01255B	C/F	ASSY COVER P-FRONT	VC17EO,ABS V0	SNA
4	6003-000010	C/F	SCREW-TAPTITE	BWH,+,B,M3,L10,ZPC(YEL),SWRCH1	SNA
4	6003-000259	C/F	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
4	AA60-00091E	C/F	SPACER-FELT	-,FELT,100X10,-,-,BLK,T0.5,-,-	SNA
4	AA60-00091K	C/F	SPACER-FELT	-,FELT,330X10,-,-,BLK,T0.35,-,-	SNA
4	AA60-00091S	C/F	SPACER-FELT	61L2,FELT,30*10,BLK,T0.5	SNA
4	BN63-01315A	C/F	COVER-FRONT MIIDDLE	LT17M2,ABS,V0	SNA
4	BN63-01316B	C/F	COVER-FRONT BEZEL	VC17EO,ABS,VO	SNA
4	BN63-01474C	C/F	FELT	VENICE 17",FELT,T0.35,20,300	SNA
4	BN64-00031A	C/F	BADGE-BRAND	RB15AS,AL,T1.4,6.3,40.1,SILIVER,SAMSUNG(G/S)	SNA
4	BN64-00254A	C/F	KNOB-FUNCTON	LT15M2,ABS,HB,BK19	SNA
4	BN67-00119A	C/F	LENS-IR	LT20M2,ACRYL,CLEAR	SA
4	BN96-01155B	C/F	ASSY BOARD P-FUNCTION IR	VE20UO,FUNCTION/IR	SNA
4	BN96-01163A	C/F	ASSY SPEAKER P	16ohm,Venice,Right,3W,300mm	SNA
4	BN96-01164A	C/F	ASSY SPEAKER P	16ohm,Venice,Left,3W,150mm	SNA
2	BN90-00656Q	-	ASSY COVER REAR	VC17EO	SNA
3	6003-001003	C/F+C/R+STD	SCREW-TAPTITE	BH,+,B,M4,L12,ZPC(BLK),SWRCH18	SA
3	BN96-01256B	C/R	ASSY COVER P-REAR	VC17EO,ABS VO	SNA
4	AA60-00091K	C/R	SPACER-FELT	-,FELT,330X10,-,-,BLK,T0.35,-,-	SNA
4	AA60-00091S	C/R	SPACER-FELT	61L2,FELT,30*10,BLK,T0.5	SNA
4	BN63-01178B	C/R	COVER-INLAY	VE15EO,PC SHEET,T0.5	SNA
4	BN63-01317A	C/R	COVER-REAR	LT17M2,ABS,V0	SNA
2	BN90-00657F	-	ASSY STAND	VC17UO	SNA
3	BN96-01335A	STD	ASSY STAND P	VC17**,ABS HB	SNA
4	6003-000259	STD	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
4	6003-001185	STD	SCREW-TAPTITE	FH,+,B,M3,L8,NI PLT,SWRCH18A	SNA
4	BN61-00811A	STD	STAND-COVER	LT15M2,ABS HB	SNA
4	BN61-00812A	STD	STAND-SUB COVER	LT15M2,ABS HB	SNA
4	BN61-00813A	STD	STAND-BRKT BOTTOM	LT15M2,SECC,T1.0	SNA
4	BN73-60002C	STD	RUBBER FOOT	VENICE 15",RUBBER,DIA 14,1.0,BLACK	SNA
4	BN96-01162B	STD	ASSY MISC P-HINGE	VC17UO,DIE CASTING T2.5	SNA

Level	Loc. No.	Code No.	Description	Specification	Remarks
2	BN91-00567H	-	ASSY LCD-S5	ES17,S5	SNA
3	BN07-00113A	CIS	LCD	LTM170EH-L05,ES17AS,1280*1024,383.5*298*15,16.19M,56,0.264*0.264,0~55,5.0,TN,-	SA
2	BN91-00801K	-	ASSY CHASSIS	VC17EO	SA

7-2-1 LW20M21C Main PCB Parts

Level	Code No.	Loc. No.	Description	Specification	Remarks
0	VE20EO				
1	CP-VE20EO	-	1	CHIMEI	-
4	BSNA97-00359Z	-	ASSSA SMD	VE20EO	SNA
5	0401-001056	D200	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D600	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D701	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D702	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D800	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D908	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D909	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D910	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D912	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D913	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D915	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D948	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D949	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D951	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D952	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D953	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D954	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D955	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D956	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0401-001056	D957	DIODE-SWITCHISNAG	MMBD4148SE,100V,200MA,SOT-23,TP	SA
5	0402-000553	D101	DIODE-RECTIFIER	SS24,40V,2.0A,DO-214AA	SA
5	0402-000553	D102	DIODE-RECTIFIER	SS24,40V,2.0A,DO-214AA	SA
5	0403-000579	D904	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D916	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D917	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D918	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D919	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D920	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D928	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-000579	D950	DIODE-ZESNAER	BZX84C5V1,4.8-5.4V,200MW,SOT-23,TP	SA
5	0403-001048	D944	DIODE-ZESNAER	BZX84C16,15.3-17.1V,225MW,SOT-23,TP	SA
5	0403-001052	D603	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D604	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D900	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D901	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D902	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D903	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D905	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D906	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D911	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D914	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D921	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D922	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D923	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D924	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D925	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D926	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D927	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D930	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D932	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D934	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D936	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	0403-001052	D940	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D941	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D942	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D945	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D946	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001052	D947	DIODE-ZESNAER	RD8.2MB,7.7-8.7V,200MW,SOT-23,TP	SA
5	0403-001425	D201	DIODE-ZESNAER	BZX84C33,31-35V,350MW,SOT-23,TP	SA
5	0403-001435	D602	DIODE-ZESNAER	QZX363C5V6,5.32-5.88V,200MW,SOT-363,TP	SA
5	0407-000123	D601	DIODE-ARRASA	DASNA202K,80V,100MA,CA2-3,SOT-23,TP	SA
5	0407-000123	D907	DIODE-ARRASA	DASNA202K,80V,100MA,CA2-3,SOT-23,TP	SA
5	0501-000280	Q801	TR-SMALL SIGSNAAL	KSA1182,PSNAP,150mW,SOT-23,TP,70	SA
5	0501-000280	Q802	TR-SMALL SIGSNAAL	KSA1182,PSNAP,150mW,SOT-23,TP,70	SA
5	0501-000280	Q803	TR-SMALL SIGSNAAL	KSA1182,PSNAP,150mW,SOT-23,TP,70	SA
5	0501-000280	Q804	TR-SMALL SIGSNAAL	KSA1182,PSNAP,150mW,SOT-23,TP,70	SA
5	0501-000342	Q200	TR-SMALL SIGSNAAL	KSC1623-SA,SNAPSNA,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q600	TR-SMALL SIGSNAAL	KSC1623-SA,SNAPSNA,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q601	TR-SMALL SIGSNAAL	KSC1623-SA,SNAPSNA,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q602	TR-SMALL SIGSNAAL	KSC1623-SA,SNAPSNA,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q603	TR-SMALL SIGSNAAL	KSC1623-SA,SNAPSNA,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q800	TR-SMALL SIGSNAAL	KSC1623-SA,SNAPSNA,200mW,SOT-23,TP,135-270	SA
5	0501-000342	Q902	TR-SMALL SIGSNAAL	KSC1623-SA,SNAPSNA,200mW,SOT-23,TP,135-270	SA
5	0501-000344	Q809	TR-SMALL SIGSNAAL	KSC1623-G,SNAPSNA,200mW,SOT-23,TP,	SA
5	0501-002080	Q100	TR-SMALL SIGSNAAL	2SC2412K,SNAPSNA,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q101	TR-SMALL SIGSNAAL	2SC2412K,SNAPSNA,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q104	TR-SMALL SIGSNAAL	2SC2412K,SNAPSNA,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q805	TR-SMALL SIGSNAAL	2SC2412K,SNAPSNA,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q810	TR-SMALL SIGSNAAL	2SC2412K,SNAPSNA,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q900	TR-SMALL SIGSNAAL	2SC2412K,SNAPSNA,200mW,SC-59,TP,120-270	SA
5	0501-002080	Q901	TR-SMALL SIGSNAAL	2SC2412K,SNAPSNA,200mW,SC-59,TP,120-270	SA
5	0801-002267	IC903	IC-CMOS LOGIC	74LCX14,-,SOIC,14P,150MIL,-,TP,-,-,-,3.6V,-40TO+85C,-,5.5V,-,-,24MA	SA
5	0801-002716	IC902	IC-CMOS LOGIC	74LCX157,MULTIPLEXER,SOIC,16P,150MIL,QUAD,TP,PLASTIC,-,-,0V,-40TO+85C,-,0V,10UA,	SA
5	0909-001036	IC706	IC-REAL TIME CLOCK	DS1337S,-,SO,8P,150MIL,400KHZ,TP,CMOS,PLASTIC,3.3V,-,-40TO+85C,-,-,-,-,-	SA
5	1001-001082	IC501	IC-VIDEO SWITCH	BA7657F,-,SOP,24P,300MIL,SISNAGL	SA
5	1003-001713	IC704	IC-LCD COSNATROLLER	GM2221,PQFP,208P,-,-,-,TR,PLASTIC,3.3V,0to+70C,-,-,-	SA
5	1103-000129	IC900	IC-EEPROM	24C02,256x8,SOP,8P,5x4mm,4.5/5.5V,0to+70C	SA
5	1103-001314	IC705	IC-EEPROM	24C16,2Kx8,SOP,8P,5x4mm,2.7/5.5V,-40to+85C	SA
5	1103-001314	IC805	IC-EEPROM	24C16,2Kx8,SOP,8P,5x4mm,2.7/5.5V,-40to+85C	SA
5	1201-001495	IC601	IC-AUDIO AMP	7050,SOP,8P,150MIL,DUAL,26DB,PLASTIC,6V,0.25W,-,40DB,-,-,20SNAA,-	SA
5	1201-001980	IC600	IC-AUDIO AMP	TDA7266D,SO,20P,16X11.1MM,-,26DB,PLASTIC,12V,25W,0TO+70C,-,-,-,-,-,TP	SA
5	1203-001816	IC109	IC-POSI.FIXED REG.	78M08,TO-252,3P,-,PLASTIC,7.7/8.3V,1.0W,-40TO+85C,0.5A,-,TP	SA
5	1203-001824	IC300	IC-VOL. DETECTOR	7042,SOT-89,3P,-,PLASTIC,4.05V/4.35V,500MW,-30TO+75C,20MA,-,TP	SA
5	1203-002842	IC101	IC-POSI.FIXED REG.	AP1117D-33A,TO-252,3P,6.7X5.6MM,PLASTIC,3.235/3.365V,-,0TO+150C,1A,-,TP	SA
5	1203-002842	IC111	IC-POSI.FIXED REG.	AP1117D-33A,TO-252,3P,6.7X5.6MM,PLASTIC,3.235/3.365V,-,0TO+150C,1A,-,TP	SA
5	1203-002844	IC105	IC-POSI.FIXED REG.	AP1117D-18A,TO-252-3L,3P,6.7X5.6MM,PLASTIC,1.764/1.836V,-,0TO+150C,1A,-,TP	SA
5	1203-002844	IC112	IC-POSI.FIXED REG.	AP1117D-18A,TO-252-3L,3P,6.7X5.6MM,PLASTIC,1.764/1.836V,-,0TO+150C,1A,-,TP	SA
5	1203-003015	IC108	IC-DC/DC COSNAVERTER	MP1410ES,SOIC,8P,4.9x3.9mm,PLASTIC,2.5/5V,-,-20to+85C,2A,-,TP	SA
5	1203-003015	IC110	IC-DC/DC COSNAVERTER	MP1410ES,SOIC,8P,4.9x3.9mm,PLASTIC,2.5/5V,-,-20to+85C,2A,-,TP	SA
5	2007-000052	R738	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R739	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R8126	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R915	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000052	R916	R-CHIP	10Kohm,1%,1/10W,TP,1608	SA
5	2007-000070	R205	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R207	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R208	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R209	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R311	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R312	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R734	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R781	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R803	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R8104	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R8105	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R837	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R841	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R842	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R845	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R850	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R851	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R856	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R857	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R859	R-CHIP	0ohm,5%,1/10W,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2007-000070	R860	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R862	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R863	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R866	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R882	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R883	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R884	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R885	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R886	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R887	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R889	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R890	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R891	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000070	R967	R-CHIP	0ohm,5%,1/10W,TP,1608	SA
5	2007-000071	R835	R-CHIP	22ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R122	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R166	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R170	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R203	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R204	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R602	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R603	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R703	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R705	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R707	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R709	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R710	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R711	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R712	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R714	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R715	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R716	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R717	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R718	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R719	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R720	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R727	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R728	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R729	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R752	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R753	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R770	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R771	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R772	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R775	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R776	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R777	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R778	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R779	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R8019	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R8108	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R871	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R880	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R881	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R900	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R901	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R905	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R907	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R910	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R911	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R912	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R920	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R921	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R923	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R950	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R951	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R952	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R954	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R955	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R956	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R957	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R958	R-CHIP	100ohm,5%,1/10W,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2007-000074	R959	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R960	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R961	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R962	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R963	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R964	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000074	R968	R-CHIP	100ohm,5%,1/10W,TP,1608	SA
5	2007-000075	R940	R-CHIP	220ohm,5%,1/10W,TP,1608	SA
5	2007-000075	R942	R-CHIP	220ohm,5%,1/10W,TP,1608	SA
5	2007-000076	R200	R-CHIP	330ohm,5%,1/10W,TP,1608	SA
5	2007-000077	R750	R-CHIP	470ohm,5%,1/10W,TP,1608	SA
5	2007-000077	R751	R-CHIP	470ohm,5%,1/10W,TP,1608	SA
5	2007-000077	R802	R-CHIP	470ohm,5%,1/10W,TP,1608	SA
5	2007-000078	R604	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R611	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R619	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R623	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R725	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R839	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R864	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R927	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R928	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R931	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000078	R932	R-CHIP	1Kohm,5%,1/10W,TP,1608	SA
5	2007-000080	R512	R-CHIP	2Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R624	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R625	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R8145	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000081	R858	R-CHIP	2.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000082	R8017	R-CHIP	3.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000082	R8106	R-CHIP	3.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000082	R934	R-CHIP	3.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R600	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R601	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R607	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R609	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R800	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R801	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R8119	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R8120	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R855	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R914	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R924	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R929	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000084	R930	R-CHIP	4.7Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R173	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R852	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000087	R853	R-CHIP	6.8Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R114	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R128	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R165	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R174	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R516	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R605	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R606	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R608	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R610	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R614	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R615	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R704	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R706	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R713	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R742	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R745	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R746	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R747	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R748	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R749	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R8121	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R8143	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R8144	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R821	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2007-000090	R879	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R933	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R944	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R965	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000090	R966	R-CHIP	10Kohm,5%,1/10W,TP,1608	SA
5	2007-000091	R167	R-CHIP	12Kohm,5%,1/10W,TP,1608	SA
5	2007-000093	R612	R-CHIP	20Kohm,5%,1/10W,TP,1608	SA
5	2007-000093	R613	R-CHIP	20Kohm,5%,1/10W,TP,1608	SA
5	2007-000093	R616	R-CHIP	20Kohm,5%,1/10W,TP,1608	SA
5	2007-000094	R202	R-CHIP	22Kohm,5%,1/10W,TP,1608	SA
5	2007-000100	R514	R-CHIP	68Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R116	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R120	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R121	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R127	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R201	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000102	R211	R-CHIP	100Kohm,5%,1/10W,TP,1608	SA
5	2007-000103	R617	R-CHIP	120Kohm,5%,1/10W,TP,1608	SA
5	2007-000107	R510	R-CHIP	470Kohm,5%,1/10W,TP,1608	SA
5	2007-000113	R838	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R843	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000113	R854	R-CHIP	33ohm,5%,1/10W,TP,1608	SA
5	2007-000121	R8109	R-CHIP	820ohm,5%,1/10W,TP,1608	SA
5	2007-000234	R896	R-CHIP	1.3Kohm,5%,1/10W,TP,1608	SA
5	2007-000239	R773	R-CHIP	1.5Kohm,1%,1/10W,TP,1608	SA
5	2007-000239	R774	R-CHIP	1.5Kohm,1%,1/10W,TP,1608	SA
5	2007-000309	790	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R620	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R621	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R788	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R789	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R827	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R830	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000309	R833	R-CHIP	10ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R732	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R733	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R740	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R817	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R818	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R819	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R836	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R840	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R849	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R897	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000402	R925	R-CHIP	150ohm,5%,1/10W,TP,1608	SA
5	2007-000458	R808	R-CHIP	18Kohm,5%,1/10W,TP,1608	SA
5	2007-000539	R828	R-CHIP	200ohm,5%,1/10W,TP,1608	SA
5	2007-000539	R831	R-CHIP	200ohm,5%,1/10W,TP,1608	SA
5	2007-000539	R834	R-CHIP	200ohm,5%,1/10W,TP,1608	SA
5	2007-000570	R926	R-CHIP	220OHM,1%,1/10W,DA,TP,1608	SA
5	2007-000608	R737	R-CHIP	240ohm,5%,1/10W,TP,1608	SA
5	2007-000643	R826	R-CHIP	270ohm,5%,1/10W,TP,1608	SA
5	2007-000643	R829	R-CHIP	270ohm,5%,1/10W,TP,1608	SA
5	2007-000643	R832	R-CHIP	270ohm,5%,1/10W,TP,1608	SA
5	2007-000659	R899	R-CHIP	27ohm,5%,1/10W,TP,1608	SA
5	2007-000708	R169	R-CHIP	3.9Kohm,1%,1/10W,TP,1608	SA
5	2007-000882	R8102	R-CHIP	4.7ohm,5%,1/10W,TP,1608	SA
5	2007-000913	R171	R-CHIP	43Kohm,5%,1/10W,TP,1608	SA
5	2007-000939	R115	R-CHIP	47Kohm,1%,1/10W,TP,1608	SA
5	2007-000965	R168	R-CHIP	5.1Kohm,5%,1/10W,TP,1608	SA
5	2007-000965	R172	R-CHIP	5.1Kohm,5%,1/10W,TP,1608	SA
5	2007-001002	R8101	R-CHIP	510ohm,5%,1/10W,TP,1608	SA
5	2007-001044	R618	R-CHIP	56ohm,5%,1/10W,TP,1608	SA
5	2007-001044	R622	R-CHIP	56ohm,5%,1/10W,TP,1608	SA
5	2007-001101	R888	R-CHIP	62ohm,5%,1/10W,TP,1608	SA
5	2007-001134	R8100	R-CHIP	68ohm,5%,1/10W,TP,1608	SA
5	2007-001164	R501	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R503	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R506	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R735	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R736	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R741	R-CHIP	75ohm,1%,1/10W,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2007-001164	R902	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R903	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R904	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R917	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R918	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R919	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001164	R946	R-CHIP	75ohm,1%,1/10W,TP,1608	SA
5	2007-001167	R906	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R908	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R909	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001167	R945	R-CHIP	75ohm,5%,1/10W,TP,1608	SA
5	2007-001179	R210	R-CHIP	8.2Kohm,5%,1/10W,TP,1608	SA
5	2011-000002	RA701	R-SNAET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA702	R-SNAET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA703	R-SNAET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA704	R-SNAET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA705	R-SNAET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000002	RA706	R-SNAET	22OHM,5%,1/16W,L,CHIP,8P,TP,3216	SA
5	2011-000881	RA800	R-SNAET	33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6x0.5mm	SA
5	2011-000881	RA808	R-SNAET	33ohm,5%,1/16W,L,CHIP,8P,TP,3.2x1.6x0.5mm	SA
5	2203-000140	C119	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C120	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C132	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C286	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C314	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C316	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C318	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000140	C334	C-CER,CHIP	1.5SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000189	C107	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C117	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C118	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C143	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C163	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C175	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C179	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C183	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C190	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C203	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C217	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C607	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C609	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C615	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C620	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C745	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C754	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C763	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C769	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C802	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C808	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C810	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C817	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C818	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C819	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C820	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C821	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C822	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C823	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C824	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C825	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C827	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C828	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C829	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C839	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C910	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C918	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C919	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C920	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C939	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000189	C940	C-CER,CHIP	100SNAF,+80-20%,25V,SA5V,TP,1608,	SA
5	2203-000236	C182	C-CER,CHIP	0.1SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C189	C-CER,CHIP	0.1SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C208	C-CER,CHIP	0.1SNAF,5%,50V,C0G,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2203-000236	C209	C-CER,CHIP	0.1SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C922	C-CER,CHIP	0.1SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000236	C933	C-CER,CHIP	0.1SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000257	C180	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C181	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C187	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C188	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C200	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C205	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C212	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C502	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C743	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C744	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C750	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C755	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C756	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C757	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C758	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C809	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C811	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C812	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C846	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C936	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000257	C938	C-CER,CHIP	10SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000491	C202	C-CER,CHIP	2.2SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000491	C611	C-CER,CHIP	2.2SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000491	C612	C-CER,CHIP	2.2SNAF,10%,50V,X7R,TP,1608,-	SA
5	2203-000626	C804	C-CER,CHIP	0.022SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000626	C805	C-CER,CHIP	0.022SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000697	C909	C-CER,CHIP	0.002SNAF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000697	C915	C-CER,CHIP	0.002SNAF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000697	C916	C-CER,CHIP	0.002SNAF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000697	C917	C-CER,CHIP	0.002SNAF,0.25PF,50V,C0G,TP,1608	SA
5	2203-000783	C900	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C901	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C907	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C908	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C911	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C913	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C931	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000783	C932	C-CER,CHIP	0.33SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C902	C-CER,CHIP	0.033SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C903	C-CER,CHIP	0.033SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C904	C-CER,CHIP	0.033SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C905	C-CER,CHIP	0.033SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C906	C-CER,CHIP	0.033SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000815	C934	C-CER,CHIP	0.033SNAF,5%,50V,C0G,TP,1608	SA
5	2203-000888	C204	C-CER,CHIP	4.7SNAF,10%,50V,X7R,TP,1608	SA
5	2203-000972	C207	C-CER,CHIP	47SNAF,10%,16V,X7R,TP,1608	SA
5	2203-001052	C813	C-CER,CHIP	0.56SNAF,10%,50V,X7R,TP,1608	SA
5	2203-001052	C814	C-CER,CHIP	0.56SNAF,10%,50V,X7R,TP,1608	SA
5	2203-001052	C816	C-CER,CHIP	0.56SNAF,10%,50V,X7R,TP,1608	SA
5	2203-001086	C727	C-CER,CHIP	0.005SNAF,0.25pF,50V,SNAP0,TP,1608	SA
5	2203-001086	C728	C-CER,CHIP	0.005SNAF,0.25pF,50V,SNAP0,TP,1608	SA
5	2203-001402	C614	C-CER,CHIP	220SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2203-001402	C617	C-CER,CHIP	220SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2203-001402	C618	C-CER,CHIP	220SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2203-001402	C621	C-CER,CHIP	220SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2203-001607	C206	C-CER,CHIP	0.22SNAF,5%,50V,SNAP0,-,1608	SA
5	2203-001652	C616	C-CER,CHIP	470SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2203-001652	C619	C-CER,CHIP	470SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2203-001656	C121	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C131	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C287	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C315	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C317	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C319	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C335	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C337	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-001656	C521	C-CER,CHIP	0.47SNAF,5%,50V,SNAP0,TP,1608	SA
5	2203-005005	C228	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C235	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2203-005005	C524	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C526	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C529	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C530	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C533	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C535	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C704	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C705	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C706	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C707	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C709	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C710	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C711	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C713	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C716	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C718	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C719	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C720	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C721	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C722	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C724	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C725	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C726	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C729	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C730	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C731	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C732	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C733	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C734	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C735	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C736	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C737	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C738	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C739	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C740	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C741	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C742	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C747	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C749	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C759	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C760	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C764	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005005	C768	C-CER,CHIP	100SNAF,10%,16V,X7R,TP,1608	SA
5	2203-005065	C600	C-CER,CHIP	1000SNAF,+80-20%,10V,SA5V,-,1608	SA
5	2203-005065	C603	C-CER,CHIP	1000SNAF,+80-20%,10V,SA5V,-,1608	SA
5	2203-005194	C714	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C715	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C748	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C751	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C752	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-005194	C753	C-CER,CHIP	220pF,10%,50V,X7R,TP,1608,-	SA
5	2203-006036	C601	C-CER,CHIP	680SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2203-006036	C602	C-CER,CHIP	680SNAF,+80-20%,16V,SA5V,TP,1608	SA
5	2402-000108	C306	C-AL,SMD	10uF,20%,16V,WT,TP,4.3x4.3x5.4	SA
5	2402-000108	C837	C-AL,SMD	10uF,20%,16V,WT,TP,4.3x4.3x5.4	SA
5	2402-000135	C605	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C610	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C835	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C836	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C935	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000135	C937	C-AL,SMD	22uF,20%,16V,GP,TP,5.3x5.3x5.4	SA
5	2402-000144	C834	C-AL,SMD	3.3UF,20%,50V,GP,TP,4.3X4.3X5.4	SA
5	2402-000170	C101	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C102	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C115	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C213	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C305	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C847	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000170	C921	C-AL,SMD	1uF,20%,50V,GP,TP,4.3x4.3x5.4,	SA
5	2402-000176	C116	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C122	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C123	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2402-000176	C124	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C125	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C126	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C127	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C128	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C129	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C130	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C508	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C509	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C512	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C514	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C517	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C518	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-000176	C838	C-AL,SMD	10uF,20%,16V,GP,TP,4.3x4.3x5.4	SA
5	2402-001006	C833	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C840	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C841	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C842	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C843	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C844	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001006	C845	C-AL,SMD	4.7uF,20%,25V,GP,TP,3.6x6.3x3.	SA
5	2402-001042	C109	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C111	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C112	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C113	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C178	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C201	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C210	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C604	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C606	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C608	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C613	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C622	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C712	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C767	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001042	C800	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	SA
5	2402-001044	C184	C-AL,SMD	100UF,20%,25V,GP,TP,8.3X8.3X6.3MM	SA
5	2402-001044	C191	C-AL,SMD	100UF,20%,25V,GP,TP,8.3X8.3X6.3MM	SA
5	2402-001070	C193	C-AL,SMD	470uF,20%,16V,GP,TP,10x10.2,-	SA
5	2402-001081	C110	C-AL,SMD	100uF,20%,25V,WT,TP,8.3x8.3x10	SA
5	2402-001086	C114	C-AL,SMD	100UF,20%,16V,WT,TP,6.6X6.6X5.3	SA
5	2402-001153	C723	C-AL,SMD	100UF,20%,6.3V,WI,TP,6.3X5.8MM	SA
5	2402-001155	C623	C-AL,SMD	47UF,20%,16V,WT,TP,6.3X5.2MM	SA
5	2409-001049	C523	C-ORGASNAIC	47UF,20%,6.3V,FX,TP,5X5.9MM,-	SA
5	2409-001049	C717	C-ORGASNAIC	47UF,20%,6.3V,FX,TP,5X5.9MM,-	SA
5	2409-001051	C194	C-ORGASNAIC	82UF,20%,6.3V,WT,TP,6.3*5.9MM,2.1	SA
5	2409-001051	C708	C-ORGASNAIC	82UF,20%,6.3V,WT,TP,6.3*5.9MM,2.1	SA
5	2409-001065	C185	C-ORGASNAIC	82UF,20%,16V,WT,TP,8X6.9MM,-	SA
5	2409-001065	C192	C-ORGASNAIC	82UF,20%,16V,WT,TP,8X6.9MM,-	SA
5	2703-000185	L803	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L804	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L902	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L903	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L904	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L905	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L908	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000185	L909	ISNADUCTOR-SMD	3.3uH,10%,2012	SA
5	2703-000222	L802	ISNADUCTOR-SMD	560SNAH,10%,2012	SA
5	2703-000392	L801	ISNADUCTOR-SMD	10uH,5%,4532	SA
5	2703-000398	L900	ISNADUCTOR-SMD	10uH,10%,3225	SA
5	2703-000398	L901	ISNADUCTOR-SMD	10uH,10%,3225	SA
5	2703-000398	L906	ISNADUCTOR-SMD	10uH,10%,3225	SA
5	2703-000398	L907	ISNADUCTOR-SMD	10uH,10%,3225	SA
5	2703-000417	L201	ISNADUCTOR-SMD	220uH,5%,3225	SA
5	2703-001426	L202	ISNADUCTOR-SMD	680uH,20%,7070	SA
5	2703-001778	FT131	ISNADUCTOR-SMD	3.3uH,20%,3225	SA
5	2703-002327	L200	ISNADUCTOR-SMD	3.9uH,5%,3225	SA
5	2801-003667	X701	CRSASTAL-SMD	14.31818MHz,30ppm,28-AASNA,16,50ohm,TP	SA
5	2801-004004	X800	CRSASTAL-SMD	20.25MHz,20ppm,28-AASNA,13pF,25ohm,TP	SA
5	2901-001114	FT104	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT105	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT106	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA

Level	Code No.	Loc. No.	Description	Specification	Remarks
5	2901-001114	FT107	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT108	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT109	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT110	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT111	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT112	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT113	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT500	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT701	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT702	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT703	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT704	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT705	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT706	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT709	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT710	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	2901-001114	FT802	FILTER-EMI SMD	25VDC,2.0ADC,-,100SNAF,3.2x1.6x1	SA
5	3301-001145	20ISNACH	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT100	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT101	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT102	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT11	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT118	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT126	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT127	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT130	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT144	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	FT200	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3301-001145	PAL	BEAD-SMD	60ohm,4516,6000mA,TP,70ohm/45MHz,82ohm/760MHz,0.01ohm	SNA
5	3704-000249	IC702	SOCKET-IC	32P,PLCC,SSNA,1.27mm	SA
5	3708-001763	CSNA702	COSNASNAECTOR-FPC/FFC/PIC	50P,0.5MM,SMD-A,SSNA	SA
5	3711-002046	CSNA905	COSNASNAECTOR-HEADER	BOX,12P,1R,1.25MM,SMD-S,SSNA,WHT	SA
5	3711-004934	CSNA705	COSNASNAECTOR-HEADER	BOX,5P,1R,1.25MM,SMD-A,SSNA,WHT	SA
5	3711-005291	CSNA601	COSNASNAECTOR-HEADER	BOX,2P,1R,2MM,SMD-A,SSNA,WHT	SA
5	3711-005292	CSNA600	COSNASNAECTOR-HEADER	BOX,3P,1R,2MM,SMD-A,SSNA,WHT	SA
5	3711-005471	CSNA907	COSNASNAECTOR-HEADER	BOX,12P,1R,1.25mm,SMD-A,SSNA+Pb,IVR	SA
5	BSNA27-00009A	FT128	COIL CHOKE	SMD 12X12X6,EOS,33UH,15%,-0.12Ω MAX,2A,DR10X5.0MM,18.5TS,12X12X6,1.8MM,1UEW 0.	SA
5	BSNA27-00009A	FT145	COIL CHOKE	SMD 12X12X6,EOS,33UH,15%,-0.12Ω MAX,2A,DR10X5.0MM,18.5TS,12X12X6,1.8MM,1UEW 0.	SA
5	BSNA41-00471A	MP1.0	PCB MAISNA	VE17UO,4,1.6,160*160,VE17	SNA
5	BSNA97-00360J	MICOM1	ASSSA MICOM	VE15EO,VCT49XSAF,P-VSNACPEU,2004-01.27,BSNA09-00006A	SA
6	BSNA09-00006A	IC802	IC MICOM	VCT4973-XM C7,144,3.3V,PAL SNAicam,PMQFP,TR,0 to +70	SNA
4	BSNA97-00362SNA	MICOM	ASSSA MICOM	VE20EO,PM39LV020,T-VSNAC20PEU,20040324,1107-001495	SNA
5	1107-001495	IC703	IC-FLASH MEMORSA	AT49BV002ASNA-70JI,256Kx8Bit,PLCC,32P,14x11.5mm,70SNAS,2.7/3.6V,-,-,-40to+85C,50uA,-	SA
2	BSNA91-00807F	-	ASSSA SHIELD	SNAEW	SNA
3	0201-001578	CIS	ADHESIVE-HM	HM-555,WHT,4,000 Cps,-	SNA
3	3809-001522	CIS	CABLE-FLAT	30V,80C,70mm,50P,0.5mm,-	SNA
3	6003-000117	SH/TUSNAER+SH/PASNA	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(SAEL),SWRCH18A	SNA
3	6003-000256	SH/PASNA+IP/PCB	SCREW-TAPTITE	BWH,+,B,M3,L10,ZPC(SAEL),SM20C	SNA
3	6003-000259	SH/PASNA+IP/PCB	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(SAEL),SWRCH18A	SNA
3	6003-000259	SH/PASNA+M/PCB	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(SAEL),SWRCH18A	SNA
3	6003-000277	SH/PASNA+C/F	SCREW-TAPTITE	BH,+,B,M3,L12,ZPC(SAEL),SWRCH18	SNA
3	BSNA44-00115A	CIS	IP BOARD	IP-51135T,VeSNAice 20",4.0mA,6.0mA,51KHZ,6,90V/264VAC,+13V/+5V,0 to +40,-20 to +60	SA
3	BSNA61-01323A	CIS	HOLDER-ISNAVERTER WIRE	VE20,ABS V0,T2.0	SNA

7-2-2 LW20M21C Others

Level	Code No.	Loc. No.	Description	Specification	Remarks
2	BSNA90-00400B	-	ASSSA STASNAD	VE20UO	SNA
3	BSNA96-01160A	STD	ASSSA STASNAD P	VE20UO,ABS HB	SA
4	6003-000122	STD	SCREW-TAPTITE	BH,+,B,M4,L12,ZPC(SAEL),SWRCH18	SA
4	6003-001010	STD	SCREW-TAPTITE	FH,+,B,M3,L6,ZPC(SAEL),SWRCH18A	SA
4	6003-001024	STD	SCREW-TAPTITE	RWH,+,B,M4,L12,ZPC(SAEL),SWRCH1	SA
4	AA63-00099C	STD	SPACER-FELT	47W3,FELT,BLK,T0.35,30*30	SNA
4	BSNA61-00816A	STD	STASNAD-COVER	LT20M2,ABS HB,SNAAT	SNA
4	BSNA61-00817A	STD	STASNAD-SUB COVER	LT20M2,ABS HB,SNAAT	SNA
4	BSNA61-00818A	STD	STASNAD-BRKT BOTTOM	LT20M2,SECC,T1.0,SNAAT	SNA
4	BSNA61-01171A	STD	STASNAD-SWIVEL BASE	VE20,ABS,T2.5,BK07	SNA
4	BSNA63-01474A	STD	FELT-STASNAD	VESNAICE 20",FELT,T1.0,10,15	SNA
4	BSNA64-00303A	STD	KSNAOB-LOCK	VE20,ABS,GR70,SV012P	SNA
4	BSNA73-60002A	STD	RUBBER-FOOT	CSA15PO,SPOSNAGE,-,-,-,BL,-,-,-,-	SNA
4	BSNA96-01161A	STD	ASSSA MISC P-HISNAGE	VE20UO,DIE CASTISNAG T2.5	SNA
2	BSNA90-00647SA	-	Fsol VE20EO	SNA	
3	6003-001003	C/F+C/R	SCREW-TAPTITE	BH,+,B,M4,L12,ZPC(BLK),SWRCH18	SA
3	BSNA96-01158B	C/F	ASSSA COVER	P-FROSNAT VE20EO,ABS V0	SNA
4	6003-000010	C/F	SCREW-TAPTITE	BWH,+,B,M3,L10,ZPC(SAEL),SWRCH1	SNA
4	6003-000276	C/F	SCREW-TAPTITE	BH,+,B,M3,L10,ZPC(SAEL),SWCH10	SNA
4	AA60-00091E	C/F	SPACER-FELT	-,FELT,100X10,-,-,BLK,T0.5,-,-	SNA
4	AA60-00091S	C/F	SPACER-FELT	61L2,FELT,30*10,BLK,T0.5	SNA
4	BSNA63-01181A	C/F	COVER-FROSNAT	LT20M2,ABS,V0,GR70,SV-012P	SNA
4	BSNA63-01182B	C/F	COVER-FROSNAT BEZEL	VE20EO,ABS VO	SNA
4	BSNA63-01474D	C/F	FELT	VESNAICE 20",FELT,T0.35,20,350	SNA
4	BSNA63-01474E	C/F	FELT	VESNAICE 20",FELT,T0.35,20,400	SNA
4	BSNA64-00207A	C/F	BADGE-BRASNAD	POSEIDOSNA,AL,T1.5,8.5,50,BLK,SILVER,SAMSUSNAG(G/S)	SNA
4	BSNA64-00254A	C/F	KSNAOB-FUSNACTOSNA	LT15M2,ABS,HB,BK19	SNA
4	BSNA67-00119A	C/F	LESNAS-IR	LT20M2,ACRSAL,CLEAR	SA
4	BSNA96-00496A	C/F	ASSSA SPEAKER P	16ohm,Ares 15",Right,3W,530mm	SNA
4	BSNA96-01155B	C/F	ASSSA BOARD	P-FUSNACTIOSNA IR VE20UO,FUSNATIOSNA/IR	SNA
4	BSNA96-01164A	C/F	ASSSA SPEAKER P	16ohm,VeSNAice,Left,3W,150mm	SNA
2	BSNA90-00656R	-	ASSSA COVER REAR	VE20EO	SNA
3	6003-001310	C/F+C/R+STD	SCREW-TAPTITE	BH,+,B,M4,L16,ZPC(BLK),SWRCH18A	SNA
3	BSNA96-01159B	C/R	ASSSA COVER P-REAR	VE20EO,ABS V0	SNA
4	AA60-00091B	C/R	SPACER-FELT	-,FELT,100X10,-,-,BLK,T0.35,-,-	SNA
4	BSNA63-01178B	C/R	COVER-ISNALASA	VE15EO,PC SHEET,T0.5	SNA
4	BSNA63-01191A	C/R	COVER-REAR	LT20M2,ABS,V0,BK19	SNA
4	BSNA63-01474F	C/R	FELT	VESNAICE 20",FELT,T0.35,10,50	SNA
2	BSNA91-00349G	-	ASSSA LCD-CP	MU20EO	SNA
3	BSNA07-00135A	LCD	LCD-PASNAEL	V201V1-T01,RubeSNAs,640*480,448.6*339.6*25,16.7M,40,0.637*0.637,0~50,5V,TSNA	SA
2	BSNA91-00801J	-	ASSSA CHASSIS	VE20EO	SNA
3	BSNA94-00539R	-	ASSSA PCB MAISNA	VE20EO	SNA
4	0204-002420	CIS3	SOLVESNAT	1M-1000,C3H70H,96,-,-	SNA
4	0204-002426	CIS4	FLUX	DF-201TVS,MIX,0.820,FLUX 13%, 14KG,-	SNA
4	2801-003959	X702	CRSASTAL-USNAIT	0.032768MHz,20ppm,28-AASA,12.5pF,35kohm,BK	SA
4	2904-001179	FT800	FILTER-SAW	36.125MHz,-,32.65-39.6MHz/0.5dB,SIP5K,+-0MHz/21.8dB,31.25MHz/37dB	SA
4	3701-001294	CSNA908	COSNASNAECTOR-DSUB	15P,3R,FEMALE,STRAIGHT,AUF	SA
4	3705-001331	CIS6	COSNASNAECTOR-COAXIAL	PAL,ADAPTOR(J/J),-,75ohm,-	SA
4	3711-004712	CSNA100	COSNASNAECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SSNA	SA
4	3722-000158	CSNA900	JACK-PISNA	1P,3.4mm,SSNA,SAEL,-	SA
4	3722-000498	CSNA902	JACK-SCART	21P,-,SSNA,BLK,SNAO	SA
4	3722-001061	CSNA909	JACK-PHOSNAE	1P,3.6PI,AG,BLK,SNA	SA
4	3722-001734	CSNA903	JACK-VHS	4P,-,SSNA,BLK,-	SA
4	3722-001846	U1913	JACK-PISNA	2P,8.3MM,AU,WHT/RED,-	SA
4	BSNA40-00049A	TU01	TUSNAER	TMQZ6-416A,VE15,PAL BG,PAL HSAPER,38.9MHz,75 ohm,75 ohm,PHOSNAE-JACK,ASSAMM,5V,TR	SA